



4K

AZSTREAMDSIGN













This a Digital Signage Streaming box android 6.0.1 This box allows you to stream a wide variety of video using 64bit, S905+ Quadcore, 2gb DDR3 RAM, 16gn EMMC ROM. Wi-Fi 802.11 b/g/n, Bluetooth 4.0, with HDMI 2.0 output for full HD 1080p and 4K Ultra HD.

Use Slideshow feature to show digital menus or use 3rd party Apps for showing Digital Signage. Play Video, show pictures, play music or operate any of your Android apps.

Applications:

- Menu Boards
- Flight Status
- Advertising
- Promotions
- Sales
- Public View Monitor
- Next In Line
- Playing Video
- and more



| | | |
|--|--|--|
|  Chipset AML S905X Quad-Core 64-bit Cortex-A53 up to 2.0GHz |  OS Android 6.0.1 |  Storage RAM: 2gb DDR3 ROM: 16gb EMMC FLASH |
|  Support Media format mkv/wmv/mpg/mpeg/dat/avi/ mov/iso/mp4/rm |  Support Music format MP3/AAC/WMA/RM/FLAC/OGG |  Support Photo format HD JPEG/BMP/GIF/PNG/TIFF |
|  OSD type of languages English /French /German /Spanish /Italian / etc multilateral languages |  Support Decoder format VP9/H.265 up to 4Kx2K@60fps, H.264/ MPEG-1/2/4 VC-1/AVS/RealVideo up to 1080p@60fps |  LAN 10/100M, standard RJ-45 |
|  Interface HDMI 2.0,CVBS LR Stereo,Ethernet-Rj45, SPDIF Digital Optical, USB 2.0x2, SD/SDHC/MMC card reader |  Control Port IR remote control port,USB mouse, USB keyboard cable port,2.4GHz air mouse radio port |  Other Power Supply: DC 5V/2A Accessory: Remote control, User manual, Power supply, HDMI cable Option: Support mouse and keyboard via USB;Support 2.4GHz wireless mouse and keyboard via 2.4GHz USB dongle |